



## FFC2R Band Pass filter

- Up to 1500W dual cavity, RF Filter for FM Radio Stations, 87.5-108MHz
- Can fit in rack cabinet, with or without optional 6RU Rack mounting panel
- Low loss, very rugged, stable tuning over time
- Compact design with minimal space required
- Conservatively rated, high quality materials & precision crafted parts
- Designed to minimize inter-mods, harmonics or spurious emissions

### Typical Specifications

Model	FFC2R
Max Power	1500W
Impedance	50 Ohm
Frequency Range	87.5-108MHz
Insertion Loss	0.20-0.45dB Max
Return Loss +/- 150kHz	≤-26dB
Rejection +/- 3MHz	Typical ≤-30dB
Connectors	7-16 Female Input/Output
Working Temperature	-4°F to 122°F
Weight	18kg/40lbs
Dimensions	800mm / 31 1/2" inches (H) 440mm / 17 1/4" inches (L) 232mm / 9" inches (W)

All features & specifications are subject to change without notice



Optional 6RU Rack Mounting Panel Shown

