



# FFC03 Band Pass filter

- Up to 300W, dual cavity RF Filter for FM Radio Stations, 87.5 -108MHz
- Optional 4RU rack mounting kit available
- Low loss, very rugged, stable tuning over time
- Compact design with minimal space required
- Conservatively rated, high quality materials & precision crafted parts
- Designed to minimize inter-mods, harmonics or spurious emissions

## Typical Specifications

Model	FFC03
Max Power	300W
Impedance	50 Ohm
Frequency Range	87.5-108MHz
Insertion Loss	-0.51dB to -0.80dB Max
Return Loss +/- 150kHz	≤-26dB
Rejection +/- 3.5MHz	Typical ≤-30dB
Connectors	N-Type Female Input/Output
Working Temperature	-4°F to 122°F
Weight	7kg/16lbs
Dimensions	770mm / 30" inches (H) 190mm / 7 1/2" inches (L) 90mm / 3 1/2" inches (W)



Optional 4RU Rack Mounting Kit Shown

All features & specifications are subject to change without notice

