



# FFTC05 Band Pass filter

- Up to 500W, triple cavity RF Filter for FM Radio Stations, 87.5 -108 MHz
- Optional 4 RU rack mounting kit available
- Low loss, very rugged, stable tuning over time
- Compact design with minimal space required
- Conservatively rated, high quality materials and precision crafted parts
- Designed to minimize inter-mods, harmonics or spurious emissions

## Typical Specifications

Model	FFTC05
Max Power	500W
Impedance	50 Ohm
Frequency Range	87.5-108MHz
Insertion Loss	-0.50 to -0.81dB Max
Return Loss +/- 150kHz	≤-26dB
Rejection +/- 1.5MHz	Typical ≤-30dB
Connectors	7-16 Female Input/Output
Working Temperature	-4°F to 122°F
Weight	25kg/55lbs
Dimensions	680mm / 26.7 inches (H) 400mm / 15 3/4" inches (L) 175mm / 7" inches (W)



Optional 4RU Rack Mounting Kit Shown

All features & specifications are subject to change without notice

