



FFTC3 Band Pass filter

- Up to 3000W, triple cavity RF Filter for FM Radio Stations, 87.5-108MHz
- Low loss, very rugged, stable tuning over time
- Compact design with minimal space required
- Conservatively rated, high quality materials & precision crafted parts
- Designed to minimize inter-mods, harmonics or spurious emissions

Typical Specifications

| | |
|------------------------|--|
| Model | FFTC3 |
| Max Power | 3000W |
| Impedance | 50 Ohm |
| Frequency Range | 87.5-108MHz |
| Insertion Loss | -0.30 to -0.42 dB Max |
| Return Loss +/- 150kHz | ≤-26dB |
| Rejection +/- 1.5MHz | Typical ≤-30dB |
| Connectors | 7/8" Flange Input/Output |
| Working Temperature | -4°F to 122°F |
| Weight | 37kg/81.5lbs |
| Dimensions | 1300mm / 51" inches (H) 610mm / 24" inches (L) 235mm / 9 1/4" inches (W) |

