



FDCSDC2 Starpoint Combiner

- 2 Channel starpoint combiner, 2 Bandpass filters per channel
- Up to 2000W power input per channel
- Low loss, very rugged, stable tuning over time, compact design
- Conservatively rated, high quality materials & precision crafted parts
- Designed to combine multiple frequencies into a single antenna system and also minimize inter-mods, harmonics or spurious emissions

Typical Specifications

Model	FDCSDC2
Number of Channels	2
Max Power input per channel	2000W
Bandpass filters per channel	2
Impedance	50 Ohm
Frequency Range	87.5-108MHz
Insertion Loss	-0.25dB to -0.4dB
Return Loss +/- 150kHz	≤-26dB
Isolation +/- 2.5MHz	Typical ≤-30dB
Input Connectors	7/8" Flange(7-16 Female on request)
Output Connector	7/8" Flange
Working Temperature	-4°F to 122°F
Weight	45kg/99lbs
Dimensions	1300 mm / 51" inches (H)
	485 mm / 19" inches (L)
	400 mm / 15.7" inches (W)

All features & specifications are subject to change without notice

