



FDCSDC01 Starpoint Combiner

- 2 Channel starpoint combiner, 2 Bandpass filters per channel
- Up to 150W power input per channel
- Optional 2RU rack mounting kit available
- Low loss, very rugged, stable tuning over time, compact design
- Conservatively rated, high quality materials & precision crafted parts
- Designed to combine multiple frequencies into a single antenna system and also minimize inter-mods, harmonics or spurious emissions

Typical Specifications

Model	FDCSDC01
Number of Channels	2
Max Power input per channel	150W
Bandpass filters per channel	2
Impedance	50 Ohm
Frequency Range	87.5-108MHz
Insertion Loss	-0.75dB to -1.5dB
Return Loss +/- 150kHz	≤-26dB
Isolation +/- 3.5MHz	Typical ≤-30dB
Connectors	N-Type Female Input/Output
Working Temperature	-4°F to 122°F
Weight	10kg/22lbs
Dimensions	355 mm / 14" inches (H)
	228 mm / 9" inches (L)
	203 mm / 8" inches (W)

All features & specifications are subject to change without notice



Optional 2 RU rack mounting kit shown